

FUSE overview for 110-120V units

Aug. 2020

T = timelag / slowblow fuse. "F" = Fast acting fuse. All fuses must be 250V and UL-listed types.

Recommended fuse type are Schurter FST series, except: *: Schurter SPT series and **: Busmann S505

NB. Note regarding "audiophile" fuses:

A fuse is actually a quite complex component, which has to both protect the device against overvoltage, spikes and intermittent dropouts – and to protect the device against consequential damage if an internal fault occurs.

If replacing a fuse, it is very important to replace with a quality fuse of same rated current, characteristics, rated voltage, breaking capacity and a suitable safety classification. It is unfortunately our impression that not all special "Hi-End" fuses comply to these parameters and have the required safety classifications.

You will not automatically loose warranty if using other fuses, but we might reject a warranty claim if the unit fails or is damaged due to use of wrong – or questionable quality – fuse types.

| Product | Location | Qty | value | size |
|---------------------------|---------------------|-----|--------|--------|
| Antileon EVO Mono | Rear panel | 1 | 15AT | 6.3x32 |
| | F501 | 1 | 400mAT | 5x20 |
| | F502,F503 | 2 | 1AF | 5x20 |
| | F504 | 1 | 1AT | 5x20 |
| | F1, F2 (cap.boards) | 4 | 1AT | 5x20 |
| Antileon EVO Stereo | Rear panel | 2 | 10AT | 6.3x32 |
| | F501 | 1 | 400mAT | 5x20 |
| | F502,F503 | 2 | 1AF | 5x20 |
| | F504 | 1 | 1AT | 5x20 |
| | F1, F2 (cap.boards) | 4 | 1AT | 5x20 |
| Antileon Signature Mono | Rear panel | 1 | 15AT | 6.3x32 |
| | F501 | 1 | 315mAT | 5x20 |
| | F502,F503,F504 | 3 | 1AF | 5x20 |
| Antileon Signature Stereo | Rear panel | 2 | 10AT | 6.3x32 |
| | F501 | 1 | 315mAT | 5x20 |
| | F502,F503,F504 | 3 | 1AF | 5x20 |
| Athena | Rear panel | 2 | 1AT | 5x20 |
| | F1 | 1 | 63mAT | 5x20 |
| | F2, F3 | 2 | 1AT | 5x20 |
| Atilla | Rear panel | 1 | 6.3AT | 5x20 |
| Colosseum | Rear panel | 1 | T16A * | 6.3x32 |
| | F1 | 1 | 100mAT | 5x20 |
| | F2 | 1 | 1AT | 5x20 |
| Diablo (250W) | Rear panel | 1 | 12.5AT | 5x20 |
| | F101-102, F201-202 | 4 | 630mAT | 5x20 |
| Diablo 300 | Rear panel | 1 | 12.5AT | 5x20 |
| | F101-102, F201-202 | 4 | 630mAT | 5x20 |
| | F3 | 1 | 1AT | 5x20 |
| | F4 | 1 | 63mAT | 5x20 |

FUSE overview for 110-120V units

Aug. 2020

T = timelag / slowblow fuse. "F" = Fast acting fuse. All fuses must be 250V and UL-listed types.

Recommended fuse type are Schurter FST series, except: *: Schurter SPT series and **: Busmann S505

NB. Note regarding "audiophile" fuses:

A fuse is actually a quite complex component, which has to both protect the device against overvoltage, spikes and intermittent dropouts – and to protect the device against consequential damage if an internal fault occurs.

If replacing a fuse, it is very important to replace with a quality fuse of same rated current, characteristics, rated voltage, breaking capacity and a suitable safety classification. It is unfortunately our impression that not all special "Hi-End" fuses comply to these parameters and have the required safety classifications.

You will not automatically loose warranty if using other fuses, but we might reject a warranty claim if the unit fails or is damaged due to use of wrong – or questionable quality – fuse types.

| Product | Location | Qty | value | size |
|----------------------|------------------------|-----|-----------|--------|
| Diablo 120 | Rear panel | 1 | 6.3AT | 5x20 |
| | F101-102, F201-202 | 4 | 630mAT | 5x20 |
| | F3 | 1 | 1AT | 5x20 |
| | F4 | 1 | 63mAT | 5x20 |
| | F5 | 1 | 1.6AT | 5x20 |
| Ethos | Rear panel | 2 | 800mAT | 5x20 |
| | F1 | 1 | 63mAT | 5x20 |
| | F2, F3 | 2 | 1.6AT | 5x20 |
| | F4 | 0 | empty | |
| | F5, F6 | 2 | 400mAT | 5x20 |
| Essence Preamplifier | Rear panel | 2 | 1AT | 5x20 |
| | F1 | 0 | empty | |
| | F2, F3 | 2 | 400mAT | 5x20 |
| | F4 | 1 | 63mAT | 5x20 |
| | F5 | 1 | 1AT | 5x20 |
| | F6 | 1 | 1.6AT | 5x20 |
| Essence Power | Rear panel | 1 | 10AT * | 6.3x32 |
| | F101-102, F201-202 | 4 | 630mAT | 5x20 |
| | F3 | 1 | 1AT | 5x20 |
| | F4 | 1 | 63mAT | 5x20 |
| Kalliope | Rear panel | 2 | 1AT | 5x20 |
| | F1 | 1 | 63mAT | 5x20 |
| | F2 | 1 | 1AT | 5x20 |
| | F3 | 1 | 2AT | 5x20 |
| Kodo | Rear panel, main | 2 | 12.5AT ** | 5x20 |
| | Rear panel, stby | 2 | 200mAT | 5x20 |
| Legato Legacy SA | Rear panel | 2 | 1AT | 5x20 |
| | F1, F2 (analog supply) | 4 | 315mAT | 5x20 |
| | F1 | 1 | 63mAT | 5x20 |
| | F2, F3 | 2 | 1AT | 5x20 |
| Mephisto Solo | Rear panel | 1 | 15AT | 6.3x32 |
| | F1, F2 | 2 | 63mAT | 5x20 |
| | F3 | 1 | 1AT | 5x20 |
| | F4 | 1 | 1.6AT | 5x20 |

FUSE overview for 110-120V units

Aug. 2020

T = timelag / slowblow fuse. "F" = Fast acting fuse. All fuses must be 250V and UL-listed types.

Recommended fuse type are Schurter FST series, except: *: Schurter SPT series and **: Busmann S505

NB. Note regarding "audiophile" fuses:

A fuse is actually a quite complex component, which has to both protect the device against overvoltage, spikes and intermittent dropouts – and to protect the device against consequential damage if an internal fault occurs.

If replacing a fuse, it is very important to replace with a quality fuse of same rated current, characteristics, rated voltage, breaking capacity and a suitable safety classification. It is unfortunately our impression that not all special "Hi-End" fuses comply to these parameters and have the required safety classifications.

You will not automatically loose warranty if using other fuses, but we might reject a warranty claim if the unit fails or is damaged due to use of wrong – or questionable quality – fuse types.

| Product | Location | Qty | value | size |
|----------------------|------------------------|-----|--------|--------|
| Mephisto Stereo | Rear panel | 2 | 10AT | 6.3x32 |
| | F1, F2 | 2 | 63mAT | 5x20 |
| | F3 | 1 | 1AT | 5x20 |
| | F4 | 1 | 1.6AT | 5x20 |
| Mikado / - Signature | Rear panel | 2 | 630mAT | 5x20 |
| | F1 | 1 | 125mAT | 5x20 |
| | F2 | 1 | 100mAT | 5x20 |
| Mirage | Rear panel | 2 | 1AT | 5x20 |
| | F1 | 1 | 400mAT | 5x20 |
| Pandora | Rear panel | 2 | 1AT | 5x20 |
| | F1, F2 (analog supply) | 4 | 315mAT | 5x20 |
| | F1 | 1 | 63mAT | 5x20 |
| | F2, F3 | 1 | 1AT | 5x20 |
| Poseidon & Pendragon | Rear panel, main | 2 | 12.5AT | 5x20 |
| | Rear panel, stby | 2 | 200mAT | 5x20 |
| Scorpio / -S | Rear panel | 2 | 630mAT | 5x20 |
| | F1 | 1 | 250mAT | 5x20 |
| Sonett | F1-2, F4-5 | 4 | 315mAT | 5x20 |
| | F3, F6 | 0 | empty | |
| Trident / Trident II | Rear panel, main | 2 | 12.5AT | 5x20 |
| | Rear panel, stby | 2 | 200mAT | 5x20 |
| Zena | Rear panel | 2 | 1AT | 5x20 |
| | F1 | 0 | empty | |
| | F2, F3 | 2 | 400mAT | 5x20 |
| | F4 | 1 | 63mAT | 5x20 |
| | F5 | 1 | 1AT | 5x20 |
| | F6 | 1 | 1.6AT | 5x20 |